Optical Engineering

OpticalEngineering.SPIEDigitalLibrary.org

Fractional Fourier transform of hollow sinh-Gaussian beams

Xun Wang
Zhirong Liu
Daomu Zhao

SPIE.

Fractional Fourier transform of hollow sinh-Gaussian beams

Xun Wang,^a Zhirong Liu,^{a,*} and Daomu Zhao^b

^aEast China Jiaotong University, Department of Applied Physics, No. 808, Shuanggangdong Street, Nanchang City, Jiangxi Province 330013, China

^bZhejiang University, Department of Physics, Hangzhou 310027, China

Abstract. The analytical expression for hollow sinh-Gaussian (HsG) beams propagating through a paraxial $ABCD$ optical system is derived and used to investigate its propagation properties in a fractional Fourier transform (FrFT) optical system. Several influence parameters of both the HsG beams and the FrFT optical system are discussed in detail. Results show that the FrFT optical system provides a convenient way for modulating HsG beams: HsG beams maintain their dark-centered distribution when the fractional order p is low, and low-ordered HsG beams lose their original dark-centered distribution more quickly than high-ordered ones when the value of p increases. Eventually all HsG beams' intensities evolve into peak-centered distributions with some side lobes located sideways. Furthermore, our results also show that HsG beam intensity distribution versus the fractional order is periodical and the period is 2. The results obtained in this work are valuable for HsG beam shaping. © The Authors. Published by SPIE under a Creative Commons Attribution 3.0 Unported License. Distribution or reproduction of this work in whole or in part requires full attribution of the original publication, including its DOI. [DOI: 10.1117/1.OE.53.8.086112]

Keywords: hollow sinh-Gaussian beam; fractional Fourier transform; laser beam shaping; propagation.

Paper 140829 received May 22, 2014; revised manuscript received Jul. 9, 2014; accepted for publication Aug. 1, 2014; published online Aug. 26, 2014.

1 Introduction

Optical beams with zero central intensity, which are called dark-hollow beams (DHBs), have recently attracted a lot of attention both experimentally and theoretically, due to their unique properties and useful applications in atomic optics, optical communication, optical trapping, and other fields.¹⁻⁴ Meanwhile, a rich variety of methods have been used to generate various DHBs, such as the transverse mode selection method,⁵ the geometrical optical method,⁶ optical holographic method,⁷ the computer-generated hologram method,⁸ and the hollow optical fibers method.⁹ In theory, several models have been proposed to describe DHBs, such as the best-known TEM_{01}^* beam (also known as a doughnut beam), high-order Bessel beams, hollow Gaussian beams,¹⁰⁻¹² etc. In 2012, Sun et al. introduced a new mathematical model called hollow sinh-Gaussian (HsG) beams to depict DHBs.¹³ Their propagation characteristics in free space were also studied.

On the other hand, fractional Fourier transform (FrFT) as the generalization of a conventional Fourier transform, was first proposed as a new mathematical tool for solving physics problems by Namias in 1980.¹⁴ Its subsequent potential applications in optics were first explored in 1993 by Mendlovic, Ozaktas, and Lohmann.¹⁵⁻¹⁷ Since then FrFT has become an active research subject in optics and has found wide application in signal processing, optical image encryption, beam shaping, and beam analysis.¹⁸⁻²³ Recently, much work has been done concerning their FrFT for various types of beams that frequently used in modern optics.²⁴⁻³⁴ However, to the best of our knowledge, no results have been reported until

now about the propagation properties of the newly proposed HsG beams in the FrFT optical system.

In this work, we derived the analytical expression for HsG beams propagating through a paraxial $ABCD$ optical system and used it to investigate its propagation properties in the FrFT optical system. The paper is structured as follows. In Sec. 2, a propagation analytical expression for HsG beams through a paraxial optical $ABCD$ system is derived. In Sec. 3, evolution of HsG beams' intensity distributions in the FrFT system and their dependent influences on several parameters are discussed in detail and numerically illustrated by using the derived equations. Finally, the main results obtained are summarized in Sec. 4.

2 Fractional Fourier Transform of Hollow Sinh-Gaussian Beams

From an optical point of view, three kinds of optical systems for performing FrFT are proposed¹⁵⁻¹⁷ and are shown in Fig. 1, which are the Lohmann I system, the Lohmann II system, and the quadratic graded index (GRIN) medium system, respectively. Here, f_s is the standard focal length, $\Phi = p\pi/2$ with p being the fractional order, and z is the axial distance between the input and output planes along the optical axis in the GRIN medium. According to matrix optics, the transfer matrix for Lohmann I optical system can be expressed as

$$\begin{aligned} R_1 &= \begin{pmatrix} A & B \\ C & D \end{pmatrix} \\ &= \begin{bmatrix} 1 & f_s \tan(\Phi/2) \\ 0 & 1 \end{bmatrix} \begin{pmatrix} 1 & 0 \\ -\sin \Phi / f_s & 1 \end{pmatrix} \begin{bmatrix} 1 & f_s \tan(\Phi/2) \\ 0 & 1 \end{bmatrix} \\ &= \begin{pmatrix} \cos \Phi & f_s \sin \Phi \\ -\frac{\sin \Phi}{f_s} & \cos \Phi \end{pmatrix}. \end{aligned} \quad (1)$$

*Address all correspondence to: Zhirong Liu, E-mail: liuzhirong_2003@126.com

Fig. 1 Three kinds of optical systems for performing fractional Fourier transform (FrFT): (a) the Lohmann I system, (b) the Lohmann II system, and (c) the quadratic graded index (GRIN) system.

For a Lohmann II optical system, the corresponding transfer matrix can be described by

$$\begin{aligned} R_2 &= \begin{pmatrix} A & B \\ C & D \end{pmatrix} \\ &= \begin{bmatrix} 1 & 0 \\ -\tan(\Phi/2)/f_s & 1 \end{bmatrix} \begin{pmatrix} 1 & f_s \sin \Phi \\ 0 & 1 \end{pmatrix} \begin{bmatrix} 1 & 0 \\ -\tan(\Phi/2)/f_s & 1 \end{bmatrix} \\ &= \begin{pmatrix} \cos \Phi & f_s \sin \Phi \\ -\frac{\sin \Phi}{f_s} & \cos \Phi \end{pmatrix}. \end{aligned} \quad (2)$$

For the GRIN medium system, the transfer matrix with quadratic index variation $n(r) = n_0[1 - r^2/(2a^2)]$, can be written as³⁵

$$R_3 = \begin{pmatrix} A & B \\ C & D \end{pmatrix} = \begin{bmatrix} \cos(z/a) & a \sin(z/a) \\ -\frac{1}{a} \sin(z/a) & \cos(z/a) \end{bmatrix}. \quad (3)$$

In Eq. (3), a denotes the radius of the GRIN medium. Obviously, Eqs. (1), (2), and (3) have the same form when $f_s = a$ and $\Phi = z/a$. Hence, the above-mentioned three optical systems have the same transfer matrix and they are equivalent for performing FrFT.

In a cylindrical coordinate system, the electric field of the HsG beams in the original plane ($z = 0$) is defined by¹³

$$E_n(r, 0) = G_0 \sinh^n \left(\frac{r}{w_0} \right) \exp \left(-\frac{r^2}{w_0^2} \right). \quad (4)$$

In Eq. (4), n ($n = 0, 1, 2, \dots$) denotes the order of the HsG beams and G_0 is a constant related to the beam power. Obviously, for $n = 0$, the beam governed by Eq. (4) is the conventional fundamental Gaussian beam with a beam

waist of w_0 . However, for $n \geq 1$, a new kind of HsG beam is obtained.

As defined by Eq. (4), the amplitude of the HsG beam is determined by the beam's order n and waist size w_0 . In order to visualize the shape of HsG beams, a preliminary demonstration is shown in Fig. 2 for HsG beams with different orders n [Fig. 2(a)] and with different waist sizes w_0 [Fig. 2(b)], respectively. All curves in Fig. 2 have been normalized to their peak intensity value. It is apparent from Fig. 2 that the irradiance profile of the HsG beam presents a single bright ring, and the central dark size increases as n and w_0 increase. Therefore, one can control the intensity distribution of HsG beams by choosing n and w_0 .

On the other hand, Eq. (4) can be rewritten in the form

$$E_n(r, 0) = G_0 \sum_{m=0}^n a_m b_m \exp \left[\frac{-(r + c_m)^2}{w_0^2} \right], \quad (5)$$

with the coefficients given by

$$\begin{aligned} a_m &= (-1)^m 2^{-n} \binom{n}{m}, \\ b_m &= \exp \left[\left(m - \frac{n}{2} \right)^2 \right], \\ c_m &= w_0 \left(m - \frac{n}{2} \right), \end{aligned} \quad (6)$$

where $\binom{n}{m}$ is a binomial coefficient. Equation (5) indicates that the n 'th order HsG beam can be generated in a laboratory by the superposition of several decentered Gaussian beams with the same waist width w_0 , whose centers are located at positions $(-c_m, 0)$, respectively.

Fig. 2 Normalized intensity distribution of hollow sinh-Gaussian (HsG) beams as a function of r , (a) for different orders n and (b) for different waist sizes w_0 .

Within the framework of the paraxial approximation, the propagation of any laser beam through an $ABCD$ optical system can be described by the generalized Huygens-Fresnel diffraction integral, known as Collins integral formula, which takes the following form in a cylindrical coordinate system:^{36,37}

$$E_n(r, z) = \frac{i}{\lambda B} \exp(-ikz) \times \int_0^{2\pi} \int_0^\infty E_n(r', 0) \times \exp\left\{-\frac{ik}{2B} [Ar'^2 - 2rr' \cos(\theta - \theta') + Dr^2]\right\} r' dr' d\theta'. \quad (7)$$

In Eq. (7), $E_n(r', 0)$ and $E_n(r, z)$ are the electric fields in the input and output planes, respectively. r' , θ' and r , θ are the radial and azimuthal angle coordinates in the input and output planes, respectively. z is the axial distance between the input and output planes along the optical axis. k is the wave number related to the wavelength λ by $k = 2\pi/\lambda$. A , B , C , and D are the transfer matrix elements of the optical system between the input and output planes, respectively.

Substituting Eqs. (5) and (6) into Eq. (7), and recalling the following integral equation:

$$J_0(t) = \frac{1}{2\pi} \int_0^{2\pi} \exp(it \cos \varphi) d\varphi, \quad (8)$$

we can transform Eq. (7) as

$$E_n(r, z) = \frac{iG_0k}{B} \exp(-ikz) \exp\left(-\frac{ik}{2B} Dr^2\right) \sum_{m=0}^n a_m b_m \times \int_0^\infty \exp\left(-\frac{ikA}{2B} r'^2\right) \cdot \exp\left[\frac{-(r' + c_m)^2}{w_0^2}\right] \cdot J_0\left(\frac{kr}{B} r'\right) \cdot r' dr'. \quad (9)$$

Expand the exponential part into a Taylor series and use the integral equation of the hypergeometric Kummer function to evaluate the beams. When $\text{Re}(\mu + v) > 0$ and $\text{Re}(a^2) > 0$, the integral equation will take the following form:³⁸

$$\int_0^\infty t^\mu \exp(-a^2 t^2) J_\nu(pt) dt = \Gamma\left(\frac{\mu + v + 1}{2}\right) \frac{p^\nu}{2^{v+1} a^{\mu+v+1} \Gamma(v+1)} \times {}_1F_1\left(\frac{\mu + v + 1}{2}, v + 1; -\frac{p^2}{4a^2}\right). \quad (10)$$

In Eq. (10), $J_\nu(x)$ stands for the ν -order Bessel function of the first kind, $\Gamma(x)$ denotes the gamma function, and ${}_1F_1(a, b; x)$ is the confluent hypergeometric function, respectively. After tedious but straightforward integration, we obtain a result as follows:

$$E_n(r, z) = \frac{iG_0k}{2B} \exp(-ikz) \exp\left(-\frac{ikDr^2}{2B}\right) \times \sum_{m=0}^n \sum_{s=0}^\infty (-1)^m 2^{-n} \binom{n}{m} \frac{(n-2m)^s}{w_0^s \cdot s!} \times \Gamma\left(1 + \frac{s}{2}\right) \cdot \left(\frac{1}{w_0^2} + \frac{ikA}{2B}\right)^{-1-s/2} \cdot {}_1F_1\left[1 + \frac{s}{2}, 1; -\frac{\left(\frac{kr}{2B}\right)^2}{\left(\frac{1}{w_0^2} + \frac{ikA}{2B}\right)}\right]. \quad (11)$$

Equation (11) is the general propagation and transformation for HsG beams through a paraxial $ABCD$ optical system, which provides a convenient and powerful tool for

Fig. 3 Normalized intensity distribution of HsG beams in the FrFT planes with different fractional orders p for Lohmann I and Lohmann II optical systems.

treating the propagation and transformation of HsG beams. Substituting Eq. (1) or (3) into Eq. (11), one obtains the analytical expression for the hollow HsG beams propagating through the FrFT optical system. Then the corresponding intensity distribution reads as

$$I_n(r, z) = E_n(r, z)E_n^*(r, z). \quad (12)$$

In the following, we investigate the HsG beam's intensity distribution evolution in the FrFT system.

3 Numerical Simulations and Analysis

According to the analytical expressions obtained in Sec. 2, in the following, we numerically investigate the properties of HsG beams propagating through the FrFT system. In the following discussion, influence factors of HsG beam order n and the fractional transform order p on the evolution of the beam's intensity distribution in the FrFT optical system are considered. Without loss of generality, we choose the calculation parameters of HsG beams as $\lambda = 0.632 \mu\text{m}$, $w_0 = 1 \text{ mm}$, and $n = 1, 3, 5, 9$.

Figure 3 depicts the normalized intensity distribution of HsG beams in several FrFT planes. For convenience of comparison, we choose the HsG beams of three different orders (i.e., $n = 1, 3, 5, 9$). It can be seen from Figs. 3(a) and 3(b) that HsG beams maintain their dark-centered distribution when the fractional order p is low, and low-ordered HsG beams lose their original dark-centered distribution more quickly than high-ordered ones when the value of p increases [see Fig. 3(c)]. Eventually all beams evolve into a peak-centered distribution with some side lobes located sideways [see Fig. 3(e)]. Furthermore, higher-ordered HsG beams have sharper center-peaked distributions. This indicates that in order to reshape the HsG beams, one can choose reasonable

Fig. 5 Evolution of the on-axis intensity of HsG beams of several orders n in the FrFT planes versus the fractional order p .

optical parameters for HsG beams in the optical FrFT system.

Figure 4 shows the normalized intensity distribution of HsG beams in different planes in the GRIN medium. In Fig. 4, we choose $a = f_s = 1 \text{ m}$; hence, the GRIN medium is equivalent with the Lohmann I and Lohmann II optical systems for performing FrFT. Obviously, in our case, the planes $z = 0.079, 1.38, 1.57, 1.76$, and 3.06 m in the GRIN medium are, respectively, equivalent to $p = 0.05, 0.88, 1.0, 1.12$, and 1.95 in the FrFT optical system. Furthermore, one can find from Fig. 4 that the intensity distribution is symmetrical about $z = 1.57 \text{ m}$ (i.e., $p = 1$).

Figure 5 shows the evolution of the normalized on-axis intensity distribution of HsG beams of several orders n in the FrFT planes versus the fractional order p . It is obvious from Fig. 5 that the dependence of the normalized on-axis intensity on the fractional order p is periodic, and the period is 2. The on-axis intensity has a maximum value when $p = 2n + 1$ and a minimum value when $p = 2n$.

Fig. 4 Normalized intensity distribution of HsG beams in different planes in the GRIN medium.

4 Conclusions

In this work, we have derived the analytical expression for HsG beams propagating through a paraxial $ABCD$ optical system and used it to investigate its propagation properties in the FrFT optical system. Several influencing parameters of both the HsG beams and the FrFT optical system are discussed in detail. Results show that the FrFT optical system provides a convenient way for modulating HsG beams: HsG beams maintain their dark-centered distribution when the fractional order p is low, and low-ordered HsG beams lose their original dark-centered distribution more quickly than high-ordered ones when the value of p increases. Eventually, all HsG beams' intensities evolve into peak-centered distributions with some side lobes located sideways. Furthermore, our results also show that HsG beam intensity distribution versus the fractional order is periodical and the period is 2. The results obtained in this work are valuable for the HsG beam shaping.

Acknowledgments

This work is supported by the National Science Foundation of China (Grant No. 11274273 and 61263010), the Jiangxi Provincial Natural Science Foundation of China (Grant No. 20142BAB212003), the Scientific Project of Jiangxi Education Department of China (Grant No. GJJ14397), and the East China Jiaotong University Startup Outlay for Doctor Scientific Research (Grant No. 09132007).

References

1. T. Kuga et al., "Novel optical trap of atoms with a doughnut beam," *Phys. Rev. Lett.* **78**(25), 4713–4716 (1997).
2. Y. B. Ovchinnikov, I. Manek, and R. Grimm, "Surface trap for Cs atoms based on evanescent-wave cooling," *Phys. Rev. Lett.* **79**(12), 2225–2228 (1997).
3. H. Ito et al., "Laser spectroscopy of atoms guided by evanescent waves in micron-sized hollow optical fibers," *Phys. Rev. Lett.* **76**(24), 4500–4503 (1996).
4. F. E. S. Vetelino and L. C. Andrews, "Annular Gaussian beams in turbulent media," *Proc. SPIE* **5160**, 86–97 (2004).
5. X. Wang and M. G. Littman, "Laser cavity for generation of variable-radius rings of light," *Opt. Lett.* **18**(10), 767–768 (1993).
6. R. M. Herman and T. A. Wiggins, "Production and uses of diffractionless beams," *J. Opt. Soc. Am. A* **8**(6), 932–942 (1991).
7. H. S. Lee et al., "Holographic nondiverging hollow beam," *Phys. Rev. A* **49**(6), 4922–4927 (1994).
8. C. Paterson and R. Smith, "Higher-order Bessel waves produced by axicon-type computer-generated holograms," *Opt. Commun.* **124**(1–2), 121–130 (1996).
9. S. Marksteiner et al., "Coherent atomic waveguides from hollow optical fibers: quantized atomic motion," *Phys. Rev. A* **50**(3), 2680–2690 (1994).
10. V. I. Balykin and V. S. Letokhov, "The possibility of deep laser focusing of an atomic beam into the Å-region," *Opt. Commun.* **64**(2), 151–156 (1987).
11. J. Arit and K. Dholakia, "Generation of high-order Bessel beams by use of an axicon," *Opt. Commun.* **177**(1–6), 297–301 (2000).
12. Y. Cai, X. Lu, and Q. Lin, "Hollow Gaussian beams and their propagation properties," *Opt. Lett.* **28**(13), 1084–1086 (2003).
13. Q. Sun et al., "Hollow sinh-Gaussian beams and their paraxial properties," *Opt. Express* **20**(9), 9682–9691 (2012).
14. V. Naimias, "The fractional order Fourier transform and its application to quantum mechanics," *J. Inst. Math. Appl.* **25**(3), 241–265 (1980).
15. D. Mendlovic and H. M. Ozaktas, "Fractional Fourier transforms and their optical implementation: I," *J. Opt. Soc. Am. A* **10**(9), 1875–1881 (1993).
16. H. M. Ozaktas and D. Mendlovic, "Fractional Fourier transforms and their optical implementation: II," *J. Opt. Soc. Am. A* **10**(12), 2522–2531 (1993).
17. A. W. Lohmann, "Image rotation, Wigner rotation, and the fractional Fourier transform," *J. Opt. Soc. Am. A* **10**(10), 2181–2186 (1993).
18. R. G. Dorsch and A. W. Lohmann, "Fractional Fourier transform used for a lens-design problem," *Appl. Opt.* **34**(20), 4111–4112 (1995).
19. M. A. Kutay and H. M. Ozaktas, "Optimal image restoration with the fractional Fourier transform," *J. Opt. Soc. Am. A* **15**(4), 825–833 (1998).
20. Y. Zhang et al., "Beam shaping in the fractional Fourier transform domain," *J. Opt. Soc. Am. A* **15**(5), 1114–1120 (1998).
21. X. Xue, H. Wei, and A. G. Kirk, "Beam analysis by fractional Fourier transform," *Opt. Lett.* **26**(22), 1746–1748 (2001).
22. H. M. Ozaktas, Z. Zalevsky, and M. A. Kutay, *The Fractional Fourier Transform with Applications in Optics and Signal Processing*, John Wiley & Sons, Chichester (2001).
23. X. Wang and D. Zhao, "Simultaneous nonlinear encryption of gray-scale and color images based on phase-truncated fractional Fourier transform and optical superposition principle," *Appl. Opt.* **52**(25), 6170–6178 (2013).
24. Y. Cai and Q. Lin, "Fractional Fourier transform for elliptical Gaussian beams," *Opt. Commun.* **217**(1–6), 7–13 (2003).
25. D. Zhao et al., "Propagation of Hermite-cosh-Gaussian beams in apertured fractional Fourier transforming systems," *Opt. Commun.* **236**(4–6), 225–235 (2004).
26. D. Zhao et al., "Propagation of flattened Gaussian beams in apertured fractional Fourier transforming systems," *J. Opt. A: Pure Appl. Opt.* **6**(1), 148–154 (2004).
27. X. Du and D. Zhao, "Fractional Fourier transform of truncated elliptical Gaussian beams," *Appl. Opt.* **45**(36), 9049–9052 (2006).
28. Z. Liu and D. Zhao, "Coherence vortex properties of partially coherent flat-topped vortex beams," *Appl. Phys. B* **106**(3), 691–700 (2012).
29. C. Zheng, "Fractional Fourier transform for a hollow Gaussian beam," *Phys. Lett. A* **355**(2), 156–161 (2006).
30. G. Zhou, "Fractional Fourier transform of Lorentz-Gauss beams," *J. Opt. Soc. Am. A* **26**(2), 350–355 (2009).
31. G. Zhou, X. Wang, and X. Chu, "Fractional Fourier transform of Lorentz-Gauss vortex beams," *Sci. China Ser. G* **56**(8), 1487–1494 (2013).
32. D. Deng, "Propagation of Airy beams through a hard-edged aperture," *Appl. Phys. B* **107**(1), 195–200 (2012).
33. B. Tang, C. Jiang, and H. Zhu, "Propagation of Bessel-Gaussian beams through a double apertured fractional Fourier transform optical system," *J. Opt. Soc. Am. A* **29**(8), 1728–1733 (2012).
34. X. Lu et al., "Experimental study of the fractional Fourier transform for a hollow Gaussian beam," *Opt. Laser Technol.* **56**(2), 92–98 (2014).
35. J. N. McMullin, "The ABCD matrix in arbitrarily tapered quadratic-index waveguides," *Appl. Opt.* **25**(13), 2184–2187 (1986).
36. S. A. Collins, Jr., "Lens-system diffraction integral written in terms of matrix optics," *J. Opt. Soc. Am.* **60**(9), 1168–1177 (1970).
37. S. Wang and D. Zhao, *Matrix Optics*, CHEP-Springer, Beijing (2000).
38. A. Erdelyi, W. Magnus, and F. Oberhettinger, *Tables of Integral Transforms*, McGraw-Hill, New York (1954).

Xun Wang received her MS degree from the Department of Physics in Dalian University of Technology, Dalian, China. She is currently an associate professor in the Department of Applied Physics at East China Jiaotong University, Nanchang, China. Her current research interests include optical wave propagation and transformation, physical optics, and information optics.

Zhirong Liu received his PhD degree from the Department of Physics in Zhejiang University, Hangzhou, China. He is currently a lecturer in the Department of Applied Physics at East China Jiaotong University, Nanchang, China. His current research interests include optical physics, optical confinement and manipulation, and wave propagation and scattering.

Daomu Zhao received his PhD degree from the Department of Physics in Zhejiang University, Hangzhou, China. He is currently a professor in the Department of Physics there. His current research interests include optical wave propagation and scattering, information security, and optical physics.